

niagara

security JACE[®] and accessories

PRODUCT DEFINITION

Niagara Security JACE is an embedded Web server that includes the Niagara Enterprise Security application. Niagara Enterprise Security is a full-featured access control and security system that includes an intuitive graphical user interface for managing access control and security. The system can be tailored for individual end users with custom reports and graphics. Optional video surveillance integration provides a single user interface for monitoring video and system status. Standard BACnet[®] and Fox drivers enable seamless control of multiple building systems from a single platform. Web-browser clients provide full configuration and operator functionality for up to 10 simultaneous users.



Niagara Security JACE is an embedded Web server with on-board I/O for controlling up to 2 access-controlled doors and 2 security zones. Scalable by adding up to 15 modules to increase the access capacity to 32 readers, the Niagara Security JACE is appropriate for small to large installations. Optional communication cards and drivers can be added to enable BACnet[®], Modbus[®], LonWorks[®] and SNMP device communications. For larger installations, the Niagara Enterprise Security Supervisor may be used to manage multiple Niagara Security JACEs for a robust, distributed system.



Niagara Security Remote Reader Module includes I/O for 2 access-controlled doors. Interfaces to Niagara Enterprise Security JACE via RS-485 port included on the Niagara Security JACE.



Niagara Security Remote Input Output Module provides 8 supervised inputs and 8 form C relay outputs. The I/O Module can be utilized for monitoring intrusion sensors, elevator controls or controlling doors which do not require a card reader. Interfaces to Niagara Security JACE via RS-485 port included on the Niagara Security JACE.



Niagara Universal Input Output Module supports 8 Universal Inputs, 4 Form A Relay Outputs and 4 0-10 VDC Analog Outputs. The Universal I/O Modules can be utilized for monitoring analog inputs, providing analog control signals and providing relay contacts when interfacing to non-security related equipment. Interfaces to Niagara Security JACE via RS-485 on optional communication card.



Intrusion Arming Keypad with LCD display and keypad for arming and disarming Intrusion Zones. Display also provides feedback to the user regarding arming status and status of individual intrusion points. Interfaces to Niagara Security JACE via RS-485 on optional communication card.



Niagara Security Enclosures are equipped with key lock, tamper switch, Din rail for easy mounting and removable cover. The medium/large enclosures are provided with a universal power supply and provide space for backup batteries. Knockouts are provided on top, bottom and sides for external connections. The enclosure interior has generous space for cable management.

powered by

niagara
framework[®]

FEATURES

Role based users – control what users view and can access or command
Threat Level Management – change building access control based on up to 255 different threat levels
Advanced Zone Management – count people in a zone, set min and max occupancy limits, require a Supervisor, and prevent passback
Intrusion Zone Management – Monitor, arm, disarm secured areas
Elevator Floor Control – Individual floor access control
Intuitive User Interface with context-sensitive help
Configurable Wiegand Formats – Support for most proximity card formats. Avoid replacing existing credentials when retrofitting systems.
Custom Reports – The information you need in the format you want
Custom Graphic / Map creation – Create custom graphics to provide operators with quick access to critical information
Video System Integration – View and control cameras from the same console as other building functions. Select associated video from the alarm console or pop-up video when alarms occur.
Database Import – import data from other access control systems or HR databases to quickly populate the database
Alarm Escalation – Escalate alarms to remote consoles or email recipients

SUPPORTED DRIVERS

Video Drivers – Milestone®, Axis®, Dedicated Micros®, Honeywell
Building Automation Drivers – BACnet®, Lonworks®, Modbus®, and SNMP

SPECIFICATIONS

Part number	Card readers	Supervised inputs	Digital inputs	Universal inputs	Relay outputs	0-10 VDC analog outputs
T-SEC-602	2	6	3	—	4 Form C	—
T-SEC-616	2	6	3	—	4 Form C	—
T-SEC-R2R	2	4	2	—	2 Form C	—
T-SEC-RIO	—	8	2	—	8 Form C	—
T-IO-16-485	—	—	—	8	4 Form A	4

RESOURCE CAPACITIES

	Niagara Security JACE 602	Niagara Security JACE 616
Reader Modules	up to 15 ¹	up to 15 ¹
I/O Modules	up to 15 ¹	up to 15 ¹
Total Readers	2 with option for 32 max ²	16 with option for 32 max ²
Universal I/O Module	4 ¹	4 ¹
Intrusion Arming Keypad	up to 6	up to 6
Total I/O	120 ² /120 ²	120 ² /120 ²
Personnel Records	20,000	20,000
Access History Records	50,000	50,000
Supports Optional Non-Security Drivers	No ³	Yes

¹ Max of 15 modules (combined reader and I/O) per T-SEC-602 or T-SEC-616

² Up to 32 readers or 120 I/O points, depending on module combination

³ T-SEC-602 may be upgraded to T-SEC-616

General Note: For systems requiring multiple controllers or greater than 32 readers, use the Niagara Enterprise Security Supervisor solution.

KEY ADVANTAGES

- Unified graphical tool set for all connected building systems
- Scalable from 2 – 32 doors
- Integrated video surveillance
- Customizable access control functions using Niagara tools
- Single embedded platform for managing multiple systems

ORDERING INFORMATION

Niagara Security JACE

Niagara Security JACE includes connections for 2 Card Readers, 6 Supervised Inputs, 4 Form C Relay Outputs, 3 Digital Inputs, 256 MB RAM/128 MB Flash, 2 10/100 Mb Ethernet ports, (1) RS-485 serial port, (1) RS-232 serial port, and 2 communication card option slots. Provides removable screw terminal connectors and status indication LEDs. Niagara Security JACE is designed for DIN rail mounting. Includes Security Appliance, Web UI and the following standard drivers: Niagara Network (Fox) Client/Server, NRIO, BACnet IP Server and oBIX Server. Supports up to 2 card readers with maximum of 32, and 20,000 personnel records 20,000 transactional history records, and intrusion and optional video drivers. Manufactured in the USA.

T-SEC-602	Niagara Security JACE licensed for 2 readers. Additional card reader expansion is purchased separately. Supports optional BAS drivers with purchase of SEC-602-UP.
T-SEC-616	Niagara Security JACE licensed for 16 readers. Additional card reader expansion is purchased separately. Supports optional BAS drivers.
T-SEC-616-DEMO	Niagara Security Demo Kit, Niagara Security JACE licensed for 32 readers. Includes BACnet, Lonworks, MODbus TCP and 16 cameras for each available video driver. Also includes Universal Power Supply, Intrusion Keypad, Mini-Prox reader and 5 prox cards. Kit is for demo use only and not for resale.
SEC-8-RDR	Niagara Security JACE 8 reader license expansion pack.
SEC-602-UP	Upgrades the SEC 602 controller to a SEC 616 supporting a minimum of 16 card readers. Optional SEC-8-RDR reader upgrades previously applied to the SEC 602 will transfer to the upgraded SEC 616 as additional readers. Upgrade also enables support for BAS drivers on the security controller.

Hardware Options

T-SEC-R2R	Includes connections for 2 Card Readers, 4 Supervised Inputs, 2 Form C Relay Outputs and 2 Digital Inputs. Contains removable screw terminal connectors and status indication LEDs. Manufactured in the USA.
T-SEC-RIO	Includes connections for 8 Supervised Inputs, 8 Form C Relay Outputs and 2 Digital Inputs. Contains removable screw terminal connectors and status indication LEDs. Manufactured in the USA.
T-IO-16-485	Includes 8 Universal Inputs, 4 Form A Relay Outputs and 4 0-10 VDC Analog Outputs Contains removable screw terminal connectors and status indication LEDs. Intended for DIN rail mounting.
T-NPB-PWR-UN	Universal Power Supply 90 - 263 V AC 50/60 Hz Auto sensing, 15 VDC, 30 watt Power Supply, DIN Rail Mountable.
NPB-2X-485	Dual Port RS-485 option card.
NPB-LON	78 Kbps FTT-10A Lon® adapter. Uses one of the two communication slots in the Niagara Security JACE. Manufactured in the USA.

Security Intrusion Keypad

SEC-INT-KP	LCD display and keypad for arming and disarming Intrusion Zones. Display also provides feedback to the user regarding arming status and status of individual intrusion points (requires a separate NPB-2X-485 RS-485 option card for the Niagara Security JACE. A maximum of 10 Display/Keypads may be added to the 485 bus on a Niagara Security JACE 6.
------------	---

Security Enclosures*

T-SEC-ENC-SML	Small enclosure with DIN rail, tamper switch and key lock. Mounting for single reader module only. Dimensions: 6"W x 9"H x 4"D. Manufactured in the USA.
T-SEC-ENC-MED	Medium enclosure with DIN rail, tamper switch, key lock and capacity for user-provided SLA batteries. Configurable options include Niagara Security JACE, (2) reader modules or remote I/O module. Universal Power Supply is included with enclosure. Dimensions: 17"W x 15"H x 4"D. Manufactured in the USA.
T-SEC-ENC-MNP	Medium enclosure without Universal Power Supply. Allows space for an additional reader module.
T-SEC-ENC-LRG	Large enclosure with DIN rail, tamper switch, key lock and capacity for user-provided SLA batteries. Enclosure includes 2 DIN rails for additional module expansion. Configurable options include Niagara Security JACE, 4 reader modules or 2 remote I/O modules. Universal Power Supply is included with enclosure. Dimensions: 17"W x 22"H x 4"D. Manufactured in the USA.
T-SEC-ENC-LNP	Large enclosure without Universal Power Supply. Allows space for an additional reader module.

*Security enclosures are not sold in EMEA

PLATFORM SPECIFICATIONS

T-SEC-602 and T-SEC-616 Platforms

- PowerPC 440 524 MHz processor
- 256 MB DDR RAM & 128 MB Serial Flash
- Battery backup
- Real-time clock

JACE Communications

- 2 Ethernet Ports - 10/100 Mbps
- 1 RS-232 Port (9 pin D-shell connector)
- 1 RS-485 (6 pin screw terminal)

JACE Operating System

- QNX RTOS
- Sun Hotspot JVM (Java Virtual Machine)
- Niagara AX

Power Supply

- NPB-PWR-UN: 100-263 VAC, 50/60 Hz, 15VDC power supply module, 30 Watt

I/O Module Communications

- 1 RS-485 (6 pin screw terminal)

Environment

- Operating temperature range: 0° to 50°C (32°F to 122°F)
- Storage temperature range: 0° to 60°C (32°F to 140°F)
- Relative humidity range: 5% to 95%, non-condensing

Agency Certifications

- FCC part 15 Class A
- CE
- UL 294*

*UL 294 not valid in EMEA

ORDERING INFORMATION

Video Drivers	
DR-AXS-AX-4	Axis IP camera driver for 4 cameras.
DR-DED-AX-4	Dedicated Micros video driver for 4 cameras.
DR-MLS-AX-4	Milestone video driver for 4 cameras.
DR-RPD-AX-4	Honeywell RapidEye™ video driver for 4 cameras.
Optional BAS Drivers	
MPD-BAC	Multi-Protocol supports 60 BACnet devices, 5 LonWorks devices, 5 Modbus TCP devices, 5 Modbus RTU devices and 5 SNMP devices.
MPD-LON	Multi-Protocol driver supports 60 LonWorks device, 5 BACnet devices, 5 Modbus TCP devices, 5 Modbus RTU devices and 5 SNMP devices.
DR-SEC-BAC-MSTP	BACnet MS/TP Driver supports 60 BACnet devices, 2000 points, 300 histories
DR-SEC-BAC-TCP	BACnet TCP supports 60 BACnet devices, 2000 points, 300 histories
DR-SEC-LON-FTT	LonWorks supports 60 LonWorks devices, 2000 points, 300 histories
DR-SEC-MDB-RTU	Modbus RTU driver supports 60 Modbus devices, 2000 points, 300 histories
DR-SEC-MDB-TCP	Modbus TCP driver supports 60 Modbus devices, 2000 points, 300 histories
Niagara Security JACE 6 Controller Upgrades and Maintenance	
SEC-J-REV	Upgrades the Niagara Security JACE to the current Niagara AX version.
SEC-J-MA	Niagara Security JACE effective for one Maintenance Term (a period of at least 12 months, as defined in Tridium's Software Maintenance Terms and Conditions). Upgrades licenses to Niagara 4 releases issued during the Maintenance Term for which the maintenance is purchased. Subject to Tridium's Software Maintenance Terms and Conditions. The Software Maintenance Terms and Conditions can be found in the Resource Library on tridium.com.

To learn more about how to purchase and install the Niagara Security JACE, or if you are an original equipment manufacturer and would like to add this to your suite of offerings, please contact us.



804.747.4771 Corporate HQ / 877.305.1745 Customer Support

tridium.com

Copyright © 2016 Tridium Inc. All rights reserved. All other trademarks and registered trademarks are properties of their respective owners.

Information and/or specifications published here are current as of the date of publication of this document. Tridium, Inc. reserves the right to change or modify specifications without prior notice. The latest product specifications can be found by contacting our corporate headquarters, Richmond, Virginia. Products or features contained herein may be covered by one or more U.S. or foreign patents. This document may be copied only as expressly authorized by Tridium in writing. It may not otherwise, in whole or in part, be copied, photocopied, reproduced, translated, or reduced to any electronic medium or machine-readable form.